

Date		Project	
Type		Part Number	



ALL-IN-ONE PERFORMANCE LIGHTING

# RENO Smart

## BLE PIR Fixture-Mounted Smart Controller

RENO SMART lighting controls use Bluetooth Low Energy (BLE) technology to manage and adjust lighting systems wirelessly. These controls typically involve sensors that detect environmental factors such as motion, ambient light, or occupancy. When a sensor detects a change, it communicates with a Bluetooth-enabled lighting system to adjust the lighting conditions accordingly—such as turning lights on or off, dimming them, or changing their color. This setup allows for flexible, remote, and automated lighting control through a smartphone or other Bluetooth-enabled devices via the Reno Smart App.



Bluetooth

## PRODUCT FEATURES



- Reno Smart Sensors are programmed/commissioned using our Reno Smart App
- Magnetic installation and buckle installation optional
- Quick connector available
- Photosensitive sensor to maintain constant lux
- IP20 Damp Location Rated
- Infrared remote control reset function available
- PIR sensing distance adjustable
- Operating temperature: -4°F to 140°F (-20°C to 60°C)
- 5 year warranty

## KEY SPECIFICATIONS


<b>Input Voltage</b>	12VDC
<b>Installation Height</b>	Up to 4M (16ft)
<b>Detection Range</b>	50M (164ft)
<b>Frequency</b>	2405-2480MHz
<b>Operating Current</b>	50mA (max)
<b>Rx Sensitivity</b>	-92dB
<b>Photosensitivity</b>	10-1000 LUX
<b>Installation</b>	Magnetic
<b>Applications</b>	Commercial, Warehouse, Retail Facilities





## SPECIFICATIONS

Order#	Model	Installation Height	Detection Range	Input Voltage
R75003	RENO-RS-BPRN-12V	Up to 4M (16ft)	50M (164ft)	12VDC

## DIMENSIONS



## DETECTION COVERAGE



## ACCESSORIES - RENO SMART NLC



R75201  
RENO-RS-GW-BCNW  
Ceiling Mounted Gateway



R75301  
RENO-RS-RC-BNNN  
5 Keys/Reset Remote  
Controller



R75302  
RENO-RS-RC-BNNG  
7-keys Smart Switch/Remote  
Control Kit with Pallet

Order#	Model	Description
R75201	RENO-RS-GW-BCNW	Ceiling Mounted Gateway
R75301	RENO-RS-RC-BNNN	5 Keys/Reset Remote Controller
R75302	RENO-RS-RC-BNNG	7-keys Smart Switch/Remote Control Kit with Pallet